

SPECIFICATIONS

GNSS Performance	
Channels	1760
GPS	L1C/A, L2P, L1C, L2C, L5
GLONASS	G1, G2, G3
BeiDou	B1I, B2I, B3I, B1C, B2a, B2b
Galileo	E1, E5b, E5a, E6, E5AltBoc*
QZSS	L1C/A, L5, L1C, L2
SBAS	L1, L5
IRNSS	L5*
L-Band*	B2b

Positioning Accuracy	
Code Differential	Horizontal: $\pm 0.25\text{m} + 1\text{ppm}$
GNSS Positioning	Vertical: $\pm 0.50 + 1\text{ppm}$
SBAS Positioning	Typically $< 5\text{m}$ 3DRMS
High Precision Static	Horizontal: $\pm 3\text{mm} + 0.1\text{ppm}$ Vertical: $\pm 3.5\text{mm} + 0.4\text{ppm}$
Fast Static and Static	Horizontal: $\pm 2.5\text{mm} + 0.5\text{ppm}$ Vertical: $\pm 5\text{mm} + 0.5\text{ppm}$
Post Processing	Horizontal: $\pm 8\text{mm} + 1\text{ppm}$
Kinematic (PPK)	Vertical: $\pm 15\text{mm} + 1\text{ppm}$
Real Time Kinematic (RTK)	Horizontal: $\pm 5\text{mm} + 0.5\text{ppm}$ Vertical: $\pm 10\text{mm} + 0.5\text{ppm}$
Network RTK (VRS, FKP, MAC)	Horizontal: $\pm 5\text{mm} + 0.5\text{ppm}$ Vertical: $\pm 10\text{mm} + 0.5\text{ppm}$
RTK Initialization	Time 2-8s, reliability $> 99.99\%$
Positioning Rate	1Hz-20Hz
Tilt Sensor	Tilt Angle: up to 60 degrees
(Inertial Measurement Unit with E-Bubble)	Accuracy: down to 2cm (Typically less than $10\text{mm} + 0.7\text{mm}/^\circ\text{tilt}$)

Data Formats	
Positioning Data	NMEA 0183, PSIC, PJK, Binary Code
Differential Correction	RTCM 2.1, RTCM 2.3, RTCM 3.0, RTCM 3.1, RTCM 3.2 (MSM), CMR, CMR+
Static	STH, Rinex 2, Rinex 3
Network	Supported VRS, FKP, MAC, Ntrip

Operation Mode	
Base	Base Internal Radio\ Base Network\ Base External Radio\ Base WIFI
Rover	Rover UHF\ Rover Network\ Rover Bluetooth
Static	Static\ PPK

UHF Radio Characteristics	
TX/RX	Transmitting and Receiving
Frequency Range	410-470MHz
Protocols	Farlink\ Trimtalk\ SOUTH(KOLIDA)
Channels	60 channels for Farlink protocol 120 channels for other protocols

Hardware	
Size	156mm*78mm
Weight	1.3kg (dual batteries included)
Data Storage	8GB SSD internal storage Support external USB storage (up to 32 GB) Automatic cycle storage Changeable record interval Up to 20Hz raw data collection

Communication	4 Indicator lights 1 Button 1 Type C USB port (USB2.0) 1 5-PIN LEMO external power port (to RS232) 1 UHF antenna port 1 Micro SIM card slot Linux OS WEB UI WIFI: 802.11 b/g/n standard Bluetooth 4.2 standard and Bluetooth 2.1+EDR Network: 4G LTE\3.5G WCDMA\2G GSM\GPRS NFC Supported USB, FTP, HTTP data communication
---------------	---

Voice Guide	Intelligent voice technology provides status indication and operation guide Chinese, English, Korean, Russian, Portuguese, Spanish, Turkish and user define
-------------	--

Environment	Operating: -30°C to $+70^\circ\text{C}$ Storage: -40°C to $+80^\circ\text{C}$
Humidity	100% condensation
Ingress Protection	IP68 waterproof, sealed against sand and dust
Shock	Survive 2m pole drop on concrete

Power	
Battery	7.2V, 3400mAh battery, two units, hot swappable
Battery Life	Base up to 10 hours Rover up to 15 - 20 hours Static up to 20 hours
USB recharge	Power Bank Supported

FIELD SOFTWARE



K Survey



Field Genius



Surv X

KOLIDA
Professional's Choice

GUANGDONG KOLIDA INSTRUMENT CO., LTD.

Add: 7/F, South Geo-information Industrial Park, No.39 Si Cheng Road, Tian He IBD, Guangzhou 510663, China
Tel: +86-20-22139033 Fax: +86-20-22139032
Email: export@kolidainstrument.com market@kolidainstrument.com http://www.kolidainstrument.com

KOLIDA
Professional's Choice

K7X

The Power to Be Your Best



- * 1760 GNSS channels, best-in-class signal tracking capability
- * GPS + GLONASS + BDS + GALILEO + QZSS
- * Centimeter level correction data through L-band
- * 2 watt Farlink radio, up to 8-10 km working range
- * Inertial Measurement up to 60° tilt angle down to 2cm accuracy
- * Dual battery hot-swappable, Up to 20 hours working

XSERIES

Craftsmanship and Quality, The Power To Be Your Best.



Quality Materials & State-Of-Art Features

Add them together, Multiply their power.

A brand new powerful UHF radio.
An inertial measurement sensor so responsive and more accurate.
The world's leading GNSS chip.
Exceptional durability.
And a huge leap in battery life.

K7X, the power to be your best.

The Only Thing That Changed Is Everything.

1760 channels

Capture satellites As many as possible

In a period of time, some GNSS satellites disappear from horizon and new satellites appear. Bigger number of satellites a GNSS receiver tracks at a time, better accuracy the GNSS can calculate. To quickly capture the new satellites that appear in the sky, GNSS receiver must reserve a big number of channels.

K7X is capable to track signal from 5 satellite constellations (GPS, Glonass, Beidou, Galileo, QZSS), process signal of up to 16 frequencies. When compared to traditional GNSS RTK, K7X's accuracy is higher, get fixed solution faster, the working performance in forest and city center is better.

